


Dia.1000*600 Two and Half Digits and Tri-color LED Countdown Timer

	Model: DX1000-3-RYG-3
	Keyword: red yellow green color led traffic light, countdown timer led traffic lights,led countdown timer traffic light.
	Application: led countdown timer traffic light Signal is widely used in road crossing, Toll Station,Parking lot to indicate whether Vehicles can go or not.
Strengths: Save energy worldwide and thus save costs by offering a series of energy-saving and efficient LED traffic lights with first-rate quality yet affordable price.	

Technical Parameters:

Color	LED Q.ty	Light Intensity	Wave Length	Power Factor	Viewing Angle	Power	Working Voltage	Housing Material
RED	819pcs	≥824cd	625±5nm	>0.9	30°	≤39W	85V-265VA C,50/60HZ; 12/24VDC	PC,UV Resistant
YELLOW	294pcs	≥397cd	590±5nm					
GREEN	504pcs	≥749cd	505±5nm					

Packing Info:

Carton Size	Q'TY	GW	NW	Wrapper	Volume(CBM)
107*67*17cm	1pcs/carton	24.37kg	21.37kg	K=K Carton	0.12

Packing List:

Part name	Light	Shade Board	M 12X80 Screw	M4X8 Screw	Using Manual	Certificate
Q'ty.(pcs)	1	3	4	8	1	2

Installation Sketch:

